



Genesis & Mega Drive (wireless connection)

- 1 – plug the receiver to the controller port on the system. LED on the receiver will start to blink
 - 2 – Press **mode** button on the controller to pair with it. Blue LED becomes solid when connection is successful
- 6 button mode <=> 3 button mode switching can be achieved by pressing **mode** button on the controller for 3 seconds. LED on the receiver will blink twice to indicate the change
 - press and hold **mode** button on the controller for 3 seconds to re-connect with a new receiver or to retrieve lost connection. Blue LED becomes solid when connection is successful

Windows/Switch (wired connection)

- connect the controller to your Windows/Switch via USB cable. Green LED becomes solid when connection is successful
- Switch system needs to be 3.0.0 or above. Then go to System Setting > Controller and Sensors > turn on Pro Controller Wired Communication

Turbo function

- 1 – hold the button you would like to set turbo functionality to and then press the **star** button to activate/deactivate its turbo functionality
 - 2 – blue LED blinks twice to indicate the success of activation/deactivation
- d-pad is not included
 - this does not apply to Switch on wired connection

battery

status –		LED indicator –
low battery mode	—————>	red LED blinks
battery charging	—————>	red LED stays solid
battery fully charged	—————>	LED turns off

- built-in 480 mAh Li-on with 35 hours of play time
- rechargeable via USB cable with 1 - 2 hour charging time

power saving

- Sleep mode - 15 minutes without use

support

- please visit support.8bitdo.com for further information & additional support

Mega Drive (无线连接)

1. 将接收器插入 Mega Drive 的手柄端口，接收器蓝灯闪烁。轻按手柄 **start** 键即可连接，连接后蓝灯常亮。
 2. 6 键 <=> 3 键 在连接状态下长按 **mode** 键 3 秒进行切换，接收器蓝灯闪烁 2 下。
- * 如连接丢失或重新适配接收器，可长按 **mode** 键 3 秒进入配对状态，蓝灯快速闪烁，连接成功后，蓝灯常亮表示配对成功。

Windows/Switch (有线连接, 有线优先)

- * 用 USB 线将手柄连接到 Windows/Switch 设备 USB 端口，连接后绿灯常亮。
- * 连接 Switch 须主机系统版本为 3.0.0 以上并启用有线连接：设置 - 手柄与感应器 - Pro 手柄的有线连接。

Turbo 连发功能

1. 按住需要设置连发的功能键，再按下星号键可开启/关闭按键的连发功能。
 2. 开启/关闭连发功能手柄蓝灯闪烁 2 下。
- * 方向键不支持连发。
 - * 有线 Switch 时不可用。

电池

电量状态		指示灯状态
电量不足	—————>	红灯闪烁
充电中	—————>	红灯常亮
充电完成	—————>	指示灯熄灭

- * 内置 480 mAh 锂电池，可持续使用约 35 小时。
- * 充电时间约 1 - 2 小时，充电完成后指示灯熄灭。

自动关机

- * 15 分钟无操作会自动休眠。

固件升级

- * 请访问 <http://support.8bitdo.cn> 了解详细信息。